

Home Complete

SKU: 650145 MSRP: \$1399.99

FEATURES

- Boosts all available networks speeds for enhanced cell signal coverage
- Offers an ideal solution for large homes up to 7,500 sq. ft.
- Supports multiple cellular devices and users simultaneously
- Works on all major Canadian carriers




- LTE** FASTEST NETWORK SPEEDS
- UP TO 7,500 sq. ft. COVERAGE
- UP TO +72 dB GAIN
- MULTI-USER WIRELESS BOOSTER

About

The weBoost **Home Complete** cell signal booster offers best-in-class performance in its price range. The Home Complete offers homeowners the ability to enhance networks speeds across all carriers throughout a large, multi-level home—up to 7,500 sq. ft. With the addition of Band 25, it also provides enhanced support for additional carriers across Canada. The Home Complete's booster and inside antenna are designed to complement contemporary décor. For ease of installation and versatility, the wall-mount brackets for the booster and inside antenna can be secured with the included 3M® Command™ strips or using screws (not included). The inside antenna also features a built-in kickstand for optional shelf placement. With donor and server ports on the top of the booster unit, the Home Complete helps prioritize cable access and organization. Users will experience faster data speeds, better voice quality, fewer dropped calls, and superior streaming capability. Like all weBoost boosters, it works on all major Canadian carriers. Comes with installation guide, 2-year manufacturer's warranty, and 30-day money-back guarantee.

Kit Includes




Coverage Area

IF YOUR OUTSIDE SIGNAL IS	YOUR BOOSTED SIGNAL MAY BE
●●●●● -89 AND LOWER About 5 bars	UP TO 7,500 sq. ft.
●●●●● -90 dB About 3 to 4 bars	UP TO 4,000 sq. ft.
●●●●● -100 dB About 1 to 2 bars	UP TO 2,000 sq. ft.
○○○○○ No existing	A signal booster likely will not work

Specifications

SKU NUMBER	650145
FREQUENCIES	Band 12/17 700 MHz Band 13 700 MHz Band 5 850 MHz Band 4 1700/2100 MHz Band 25/2 1900 MHz
MAX GAIN	72 dB
IMPEDANCE	75 Ohm
POWER	110-240V AC, 50-60 Hz, 20 W
CONNECTORS	F-Female
BOOSTER DIMENSIONS	8.25 x 6 x 2.4 in
BOOSTER WEIGHT	1.55 lbs

Installation



- 1 Receives signal:** The outside antenna reaches out to access the existing strong outdoor cell signal and delivers it indoors to the booster.
- 2 Boost signal:** The booster receives the signal, amplifies it, and serves as a relay between your phone and the nearest cell tower.
- 3 Broadcasts signal:** Your devices get a stronger signal, and calls and data are fed through the booster back to the network.

Available Accessories

Optional Antenna Kits



Inside Panel Antenna with mount (314444)



Outside Directional Antenna with mount (314445)



75' RG-11 Extension Cable with F Male Connectors (951175)



Splitters 75 Ohm (850034, 850035, 850036)



Lightning Surge Protector 75 Ohm (859992)

Package Dimensions

17.75 L x 12.25 W x 12.25 H



FRONT



SIDE



TOP/BOTTOM



WEIGHT

MASTER CARTON: 25 L x 20 W x 15 H | 36.60 Lbs. | Qty 2

Support

2-Year Warranty from Purchase.

Website: www.weboost.ca/support

Phone: +1 866 294 1660
Monday to Saturday



ASSEMBLED IN THE USA



Innovation, Science and Economic Development Canada

UPC

